



Doxa

Doxa Self-Test Exit sign with multiple mounting positions, up legend

The Kosnic Doxa LED emergency exit sign is a self-contained, multi-purpose, maintained or non-maintained 3-hour emergency exit sign solution. The fitting is adaptable to be surface mounted in multiple positions, suspended or recessed mounted when used with the additional suspension kit or recessed kit. It is supplied with the upward arrow exit sign.

DOX0103UP/ST ()

Specification

Voltage	220-240 Vac 50-60 Hz
Current (mA)	30
Rated Power (W)	3
CCT Words	Day Light
CCT (K)	6500
Total Luminous Flux (lm)	50 (maintained mode) 30 (emergency mode)
Nominal Lifetime (h)	40000
Power Factor	0.43
Ambient Temperature Range (°C)	0 to 40
Weight (kg)	367
In-rush current (peak/duration) (A)	12.8/116
Protection Rating	Class II
IP Rating	IP20
Battery Capacity	2600 mAh
Battery Charging Time	12 hours
Battery Code	KBAT2600LI1
Battery Life	4 years
Battery Type	Li-Ion
Battery Voltage	3.7 V
Battery Warranty	4 Years
Emergency Operation Test	Self-Test (ATS Type S)
Emergency Conversion Time	1 second
Emergency Operating Time	3 hours
On-Site Warranty	2 Years

Light Source Specification

Lumen Maintenance Factor (x.xx)	0.75
---------------------------------	------

Optional Gears and Accessories

Accessories 1

Exit Sign Left/Right EESN02-PSLR

Accessories 2

Li-ion Battery KBAT2600LI1

Technical Drawings

