



Under lights

## Belum

### Belum Self-Test emergency exit sign 1W/5W 6500K

Available April 2023 Belum • Hidden slot at the frame for attaching exit sign film • Maintained and non-maintained options • Available in self-test version • Emergency lights under the fitting illuminate the door way • All legends included

**BEL0105/ST (07238)**

## Specification

In-rush current (peak/duration) (A)	12.4 A / 120 $\mu$ s
Battery Warranty	4 Years
Notes	Mounting - Surface
On-Site Warranty	2 Years

## UEM/EME

UEM/EME Input Power (Max) (W)	5
UEM/EME Input Voltage	220-240 Vac 50-60 Hz
UEM/EME Input Current (mA)	35
UEM/EME Output Wattage (W)	1
UEM/EME Protection	Class I, IP20
UEM/EME Battery Code	KBAT2600LI1
UEM/EME Battery Type	Li-Ion
UEM/EME Battery Voltage	3.7
UEM/EME Battery Capacity (mAh)	2600
UEM/EME Battery Charging Time (h)	24 hours
UEM/EME Battery Life (Years)	4
UEM/EME Emergency Conversion time (s)	1 second
UEM/EME Emergency Operation time	3 hours
UEM/EME Emergency Operation Test	Self-Test (ATS Type S)
UEM/EME Dimensions (L x W x D) (mm)	194 x 391 x 53
UEM/EME Weight	1.08 kg
UEM/EME Ambient Temperature Range (°C)	0 to 40
UEM/EME Power Factor	0.57
UEM/EME Luminous Flux	Without Exit Sign - Maintained Mode 140 lm / Emergency Mode 140 lm, With Exit Sign - Maintained Mode 70 lm / Emergency Mode 70 lm
UEM/EME LMF at Nominal Lifetime	0.75
UEM/EME CCT	6500k Day Light

UEM/EME Warm-up time to 60%

Instant full light

Notes

Mounting - Surface

UEM/EME Lifetime (h)

40000

## Optional Gears and Accessories

Accessories 1

Battery KBAT2600LI1

## Technical Drawings

