

LL

Energy Saving GX53 Range Stainless Steel Triangle Fixture

TR-7W-SS-LL


Specifications:

Input Voltage	Rated Power	Size(L×W×H)
220-240V~ 50Hz	9W Max	160×170×52mm
110-130V~ 60Hz	8W Max	

Signs and symbols:

 Insulation of class II means double insulation.No earthing needed.

 Protected against solid objects larger than 12mm.

 After the implementation of the European Directive 2002/96/EU in the national legal system,the following applies:
Electrical and electronic devices may not be disposed of with domestic waste.

Consumers are obliged by law to return electrical and electronic devices at the end of their service lives to the public collecting points set up for this purpose or point of sale.Details to this are defined by the national law of the respective country.This symbol on the product,the instruction manual or the package indicates that a product is subject to these regulations. By recycling, reusing the materials or other forms of using old devices, you are making an important contribution to protecting our environment.



Installation:

1. Before begin any installation,disconnect electrical power at main power supply.
2. Connect downlight flylead to main supply,ensuring that connection is correct and secure.
3. Fix the triangle on the ceiling by cross-screwdriver.
(2 pieces standard screws ST3,0×12 are supplied.)
4. Slide fitting into the triangle hole and ensure to connect the desired surface.
5. Insert GX53 lamp by twisting clockwise.
6. Connect electrical power at main power supply.

Replace the bulb:

1. Disconnect electrical power at main power supply.
2. Unlock bulb by twisting anti-clockwise and remove by pulling down.
3. Replace with identical bulb of equal wattage by twisting clockwise.
4. Connect electrical power at main power supply.

CAUTION:

Please read these instructions carefully prior to installation and retain for future.

Switch off electrical power at mains.

Do not exceed the rated max. load of the bulb on the packaging.

This fitting can not be installed into a completely closed space.

Use the lamp with correct fixtures. Not suitable for bathrooms etc.

Do not touch the fitting whilst it is running or cooling down.

If in doubt consult a qualified electrician.

Double check voltage and wattage to be sure.

