

# PowerPort

For functional discreet power & charging

## POP-UP SOCKET - INSTALLATION & OPERATION INSTRUCTIONS

3 x UK Plug Sockets - MAX: 3250W

2 x USB Power Supply 2 x 500ma

Product Code: POW-2S

### INSTALLATION

1. Cut out a 102 - 105mm diameter hole in work surface.
2. Ensure there is sufficient space under the surface for the unit when it is in the closed position.
3. Remove the locking ring from the collar by rotating it in an anti-clockwise direction.
4. Insert socket into the hole.
5. Place the locking ring onto the collar and rotate clockwise to tighten against the underside of the work surface.
6. Connect the socket to power supply using the pre-wired UK plug.

### OPERATION

1. To use the **PowerPort** socket press the lid and it will pop up allowing you to gently pull up the unit until it engages into position.
2. The **PowerPort** socket is now ready for use.
3. Close the unit by gently pushing on the lid to disengage the locking mechanism.

### MAINTENANCE & CARE

1. Always disconnect the **PowerPort** prior to cleaning.
2. Periodically wipe over with soft cloth.
3. Do not use harsh chemical cleaning products as it may damage the finish.

**ATTENTION:** Please ensure when using the USB power supply, do not use devices that exceed the stated amperage.