

Fitting the Ikon Pro:

Step 1 - Drill hole to the correct size

Step 2 - From below, push the wiring loom through the hole (without head)

Step 3 - Place weather protective cap onto the socket

Once the decking is complete:

Step 4 - Place the LED heads onto the loom

Step 5 - Let the cap fall through the hole & firmly push the head into place. Repeat for all heads

Step 6 - Push the plug in and switch on to test

This product is operated by a small RF remote control. It has a maximum range of 10m, though this can be affected by walls and other solid objects. The remote control has four buttons. One turns the unit on and off. One allows you to step through the colours in the following sequence; yellow, white, red, green, blue, purple and light blue. The next press will make the controller step through all the colours, and another press of the button, will move through the colours gradually. The other two buttons allow you to set the brightness of the LEDs as required.

The Ikon Pro RGB ground light kit contains: 1 x 12V outdoor inline transformer with 2 metre extension lead, 10 x IP44 LED light fittings each with 1.5 (1.2 & 0.3) metres of cable, 1 x RF controller and 1 x 12V type 23A battery.

Max of 10 metre range for the remote control.

Not suitable to be used with timers or PIR sensors.